

# Smartbox Grid Pad Pro Specifications



**The powerful communication aid with environmental control, flexible mounting and innovative sound.**

- Three sizes to suit your needs
- Built in switch ports and high quality speakers
- Radio and infrared environment control

Powered by Grid 3, our award winning AAC software with symbol and text communication, computer control, interactive learning and more.

Features	Pro 11	Pro 13	Pro 18
Operating system	Windows 10	Windows 10	Windows 10
Software	Grid 3	Grid 3	Grid 3
Processor	Intel Core M-5Y10c CPU 1.9GHz	Intel Celeron 2957U 1.40GHz	Intel Pentium Quad Core N3700 2.2GHz
Memory	4GB	8GB	8GB
Hard drive	128GB	256GB SSD	500GB
Video card	Intel HD Graphics	Intel HD Graphics	Intel HD Graphics
Dimensions	310x200x50mm 12.2x7.8x2inch	344x216x57mm 13.5x8.5x2.2inch	440x325x50mm 17.3x12.8x2inch
Weight	1kg 2.2lbs	2.68kg 5.9lbs	2.75kg 6lbs
Battery life	Up to 6 hours	Up to 8 hours - hot swap battery available	Up to 5 hours
Tablet camera	2MP front, 5MP rear	2MP front, 8MP rear	HD Camera
Screen	11.6" 1080 HD display	13.3" 1080 Full HD display	17.3" 1080 full HD display
Access	Touchscreen, switch, USB input	Touchscreen, switch, USB input	Touchscreen, switch, USB input
Connectivity	Wi-fi, bluetooth	Wi-fi, bluetooth	Wi-fi, bluetooth
Ports	2xUSB 2.0, 1x USB 3.0 speaker out, Micro SD, mini HDMI, Auditory feedback socket	2xUSB 2.0, 3.5 speaker out, Mic in, Auditory feedback Port	2xUSB 2.0, 3.5 speaker out, HDMI, Micro SD, Auditory feedback Port
Buttons	Power, home, volume	Power, Volume	Power, Volume
Switch access	2x3.5mm jacks, radio switch (additional extra)	2x3.5mm jacks, radio switch (additional extra)	2x3.5mm jacks, radio switch (additional extra)
Amplified Speaker	2xbuilt-in high quality speakers	2xbuilt-in high quality speakers	2xbuilt-in high quality speakers
Case	Fujitsu Q665 Stylistic TPU Tough Case	-	-
Mounting plate	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible
Environment control	Servus inside - Gewa, Eldat or z-wave radio switch receiver	Servus inside - Gewa, Eldat or z-wave radio switch receiver	Servus inside - Gewa, Eldat or z-wave radio switch receiver
Wheelchair mounting	REHADapt and Daessy plate with table stand	REHADapt and Daessy plate with table stand	REHADapt and Daessy plate with table stand